

Quick Installation Guide

DK31/32CJ-FC

Specifications

	DK31CJ-72	DK32CJ-36	DK32CJ-18
Formatted Capacity*(Gbytes)	73.9	36.9	18.4
Bytes per Sector	512	512	512
#Cylinders/#Heads/#Disks	15154/24/12	15154/12/6	15154/6/3
Maximum LBA*(Hex)	89B88FF	44DC47F	226E23F
Seektime:Average(Read/Write)(ms)	5.6/6.5	5.2/6.0	5.2/6.0
Spindle Speed rpm	10025	10025	10025
Interface Type	SCSI Ultra	160 SCSI Ultra	160 SCSI Ultra 160
Transfer rate (MB/s)	160 max	160 max	160 max
Operating Temperature (C/F)	5-50°/41-122°F	5-50°/41-122°F	5-50°/41-122°F
Power: 12Vpeak(Typ)/5V peak (Typ) (A)	3.25/1.2	2.2/1.2	2.3/1.2
Start Time(s)	25	25	25

Handling Precautions

- Do not press on the drive. Hold the drive by the sides only, do not apply any force to the drive during handling or installation
- Always handle the drive with care to prevent damage from shock, vibration or electrostatic discharge (ESD). Do not touch the Printed Circuit Board (PCB).
- Electrostatic Discharge. Static electricity can damage the drive. Before handling the drive, touch an unpainted metal surface for a few seconds to drain any static electricity from your body.
- Keep the original packaging and static-protective bag in case the drive has to be returned.

Mounting Orientation

- Installation horizontal or vertical (6 directions)
- Provide adequate air flow to cool drive
- Use 4 mounting screws (6x32 UNC). Maximum screw penetration 3.8mm (0.15 in) into drive

Connector Layout

